


# PASS KAIROS Activation Manual





# Activation Procedure (standard flow chart\*1)

2/28







# Table of Contents

3/28

Procedure	Items to use					Remark
	 Activation PC	 GUI PC	 USB memory	 Kairos Core	Information	
<b>Preparation</b>						
<b>0. Preparation of equipment and software</b>	✓	✓	✓	✓	Software License	
<b>User Registration &amp; GUI PC Registration</b>						
<b>1. PASS KAIROS User Registration</b>	✓					
<b>2. Download Kairos Creator</b>	✓		✓			
<b>3. Kairos Creator installation, Get GUI PC System ID</b>		✓	✓			
<b>4. GUI PC registration</b>	✓				GUI PC name	Any string, up to 16 alphanumeric
<b>Kairos Creator setup</b>						
<b>5. Kairos Creator registration</b>	✓				Software License	Kairos Creator software license
<b>6. Kairos Creator activation</b> [Link to GUI PC]	✓		✓		GUI PC System ID	
<b>7. Kairos Creator certificate file installation</b>		✓	✓			
<b>Kairos Core Registration</b>						
<b>8. Get Kairos Core System ID and Serial number</b>		✓		✓		
<b>9. Kairos Core registration</b>	✓				Kairos Core Serial number	
<b>Kairos Core Option software setup</b>						
<b>10. Option software registration</b>	✓				Software License	Option software license
<b>11. Option software activation</b> [Link to Kairos Core]	✓		✓		Kairos Core Serial number Kairos Core System ID	
<b>12. Option software certificate file installation</b>		✓	✓	✓		

# Table of Contents / Supplement : Activation procedure for Touch Control Panel 4/28

Procedure	Items to use					Remark
	Activation PC 	GUI PC 	USB memory 	Kairos Core 	Information	
<b>Touch Control Panel setup</b>						
<b>2. Download Touch Control Panel</b>	✓		✓			
<b>13. Touch Control Panel installation, Get GUI PC System ID</b>		✓	✓			
<b>14. GUI PC registration</b>	✓				GUI PC name	Any string, up to 16 alphanumeric
<b>Touch Control Panel setup</b>						
<b>15. Touch Control Panel registration</b>	✓				Software License	Touch Control Panel software license
<b>16. Touch Control Panel activation</b> [Link to GUI PC]	✓		✓		GUI PC System ID	
<b>17. Touch Control Panel certificate file installation</b>		✓	✓			

A similar procedure to the Kairos Creator activation procedure is required.  
It is also possible to activate on the same PC as Kairos Creator.

# 0. Preparation of equipment and software

5/28

## Items to use (equipment, software)

- (1) Download Kairos Creator application from PASS Kairos and install it on GUI PC.
- (2) Register equipment and software license to PASS KAIROS.
- (3) Link equipment and software in PASS KAIROS, execute activation, and get the certificate file.
- (4) Install the certificate file with Kairos Creator application, and activate the optional function.

**PASS**

## Software License

《 Kairos Creator 》

**AT-SFC10** : GUI SW Client License

《 Kairos Touch Control Panel 》

**AT-SFTC10** : GUI License (GUI Software for Windows)

《 Kairos Core Option Software 》

**AT-SF001** : 4K

**AT-SF002** : I/O


**AT-SF003** : Canvas

**AT-SFE01** : ROSS Overdrive Connection

**AT-SFE02** : KST Connection

**AT-SFE03** : NMOS

(2) Register software license to PASS KAIROS



# 1. PASS KAIROS User Registration

6/28

## Items to use




Activation PC


1) Access to PASS KAIROS website.

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)


2) Click "Register now" button.



3) Input e-mail address and password, then click "Next" button.



4) After user profile input, please read and agree with PASS membership rule. Click "Register" button.



5) Confirm your profile and click "Register" button. Logout from PASS system automatically.

6) You will receive an email of "Registration notice". Please access the URL in the email and complete the registration process.

## 2. Download Application software

7/28

### Items to use



**Activation PC**




**USB memory**

1) Login to PASS KAIROS.(w/ ID, password)

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)

2) Click “Download” link at the side bar menu.



3) Download Application software (Kairos Creator software, etc.) in the Activation PC.  
 (“Downloads” folder etc.)

4) Copy the application software in the USB memory.  
 (xxx-setup.exe)

### 3. Kairos Creator installation, Get GUI PC System ID

8/28

#### Items to use



GUI PC




USB memory


xxxx\_setup.exe

1) Launch the GUI PC and execute Kairos Creator installer.  
(kairos-creator-xxxx-setup.exe)

2) Launch Kairos Creator application.



3) Double clicking on the System-Id string in the About screen,  
select "COPY" with mouse right click.  
Get the GUI PC System ID. (memo)



GUI PC  
System ID  
(memo)

GUI PC System ID (16 alphanumeric characters) will be used in the process of "5. Registration of Kairos Creator". Please store this information in the electric file.

4) Close the Kairos Creator application.



# 4. GUI PC registration

9/28

Items to use




Activation PC


1) Login to PASS KAIROS.(w/ ID, password)

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)

2) Click “Hardware” button at the side bar menu.




3) Select Country/Area.



4) Input necessary information.


Shop, Country, Model number(CREATOR),  
Serial number(PC name), Date of purchase, Purpose



Select “CREATOR” as a Model number.  
Register any string up to 16 alphanumeric characters for the PC name as a Serial number.

Already registered PC names cannot be used. (including other users’) If they are duplicated, an error message will be displayed. Please change the PC name.

5) Click “Complete registration” button.



\*\*\*  
Please refer to the Remark.

6) Log out form PASS KAIROS system automatically.  
An email of registration notice will be sent to you.

[Remark]  
You can also register other equipment and license by using “\*\*\*” marked buttons. However, only the GUI PC is registered here.  
For other equipment and licenses, please use the “Modify/add equipment” and “Modify/add license” screens described on the following pages.

# 5. Kairos Creator registration

10/28

Items to use



Activation PC

1) Login to PASS KAIROS.(w/ ID, password)

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)

2) Click "Modify/add license" link at the side bar menu.

4) Click "OK" button and software license registration completed.

Registration completed

3) Input necessary information and click "Add" button.

Shop, Country, Model number(AT-SFC10),  
Key Code, Date of purchase, Purpose

\*Select "AT-SFC10" in the Model number drop-down list

Software License

AT-SFC10  
Kairos Creator

# 6. Kairos Creator activation [Link to GUI PC] (1/2)

11/28

## Items to use



## Activation PC


GUI PCの  
System ID  
(memo)


\*\*GUI PC and Kairos Creator need to be registered.

1) Login to PASS KAIROS.(w/ ID, password)  
[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)


2) Click "Search equipment" link at the side bar menu.

3) Click "Search" button to display a list of registered products.


Click  button in the "Unit model" column of the "AT-SFC10" line.




4) Select the target PC name in the "Unit model" drop-down list, and click "Update" button.




Link Kairos Creator software license (AT-SFC10) to GUI PC.

5) Click  button in the "SW Relations" column of the "CREATOR" line.



6) Input GUI PC System ID and click "Update" button.



System ID : 16 alphanumeric characters (fixed length)

After performing the activation issuing the certificate file in the following step 7) and 8), the setting made in step 4) and 6) cannot be changed. Open the "License Attached" screen in step 5), and please check the settings again.

- In case the link between the license and CREATOR(PC) is incorrect: Click the "Release" button on the "License Attached" screen and set again from step 3).
- In case the value of System ID is incorrect: Edit the value of System ID on the "License Attached" screen.

## 6. Kairos Creator activation [Link to GUI PC] (2/2)

12/28

Items to use




Activation PC



USB memory

[Continuation from the previous page](#)

7) Click  button in the "Certification" column of the "CREATOR" line.



It will be in the standby state for execution of activation and issuance of registration certificate.

8) Click "OK" button to move to the "Certification download" screen.  
Download certificate file in the Activation PC.  
("Downloads" folder etc.)



9) Copy the certificate file in the USB memory.  
(Creator\_xxxx\_Certification.LST)

The System ID registered in step 6) is described in "xxxx" part.  
This certificate file can only be installed on a CREATOR with a System ID of "xxxx".

# 7. Kairos Creator certificate file installation

13/28

## Items to use




GUI PC




USB memory

Creator\_xxxx\_  
Certification.LST


- 1) Launch the Kairos Creator application.  
Click "Select" on the About screen.




- 2) Select the certificate file created in the process of "Kairos Creator activation"  
(Creator\_xxxx\_Certification.LST)



- 3) Click "Install".



- 4) Kairos Creator launches and installation complete.



# 8. Get Kairos Core System ID and Serial number

14/28

## Items to use

GUI PC


Kairos Creator  
(GUI software)

LAN cable


Kairos Core  
AT-KC100

1) Launch the KAIROS system. (Please refer to KAIROS USER MANUAL)

2) Open "About" screen of Kairos Creator application.  
Help --> About ...




3) Double clicking on the System-Id string (Connected Sever side), select "COPY" with mouse right click.  
Get Kairos Core System ID. (memo)



4) Get Kairos Core serial number information of the label attached to the top of Kairos Core unit. (memo)



 Kairos Core  
Serial Number  
(memo)

 Kairos Core  
System ID  
(memo)

# 9. Kairos Core registration

15/28

Items to use



Activation PC

- 1) Login to PASS KAIROS.(w/ ID, password)  
[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)
- 2) Click "Modify/add equipment" link at the side bar menu.

- 4) Click "OK" button and registration completed.

- 3) Input necessary information and click "Add" button.  
Shop, Country, Model number(AT-KC100),  
Serial number, Date of purchase, Purpose

\*\* Select "AT-KC100"  
in the "Model number list" screen

Kairos Core  
Serial Number  
(memo)

# 10. Option software registration

16/28

Items to use



Activation PC

- 1) Login to PASS KAIROS.(w/ ID, password)  
[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)
- 2) Click "Modify/add license" link at the side bar menu.

- 3) Input necessary information and click "Add" button.  
Shop, Country, Model number,  
KeyCode, Date of purchase, Purpose

\*Select "AT-SFxxx" or "AT-SFExx"  
in the Model number drop-down list

- 4) Click "OK" button and software license registration completed.

Registration completed

- 5) If you purchased multiple option software, please repeat step 3) and step 4).

Software License

AT-SFxxx  
AT-SFExx



# 11. Option software activation [Link to Kairos Core] (1/3)

17/28

## Items to use



Activation PC



USB memory


**\*\*Kairos Core and option software need to be registered.**


1) Login to PASS KAIROS.(ID, password)


[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)

2) Click "Search equipment" link at the side bar menu.


3) Click "Search" button in the "Your Equipment•Linking equipment and software" screen to display a list of registered products.




4) Click  button in the "Unit model" column of the option software line.




5) "Parent Product Settings" screen  
Select the Serial number of target Kairos Core in the "Unit model" drop-down list.




6) Click "Update" button,  
and click "OK" button in the confirmation screen.

7) When there are multiple optional software,  
click  button in the "Unit model" column and repeat selecting parent product.



Parent Product Settings completed

 Kairos Core System ID (memo)

 Kairos Core Serial Number (memo)

[Continued on next page](#)

# 11. Option software activation [Link to Kairos Core] (2/3)

18/28

Items to use





Activation PC













USB memory


[Continuation from the previous page](#)

8) After selecting the parent product of the option software, click  button in the "SW Relations" column of the "AT-KC100" line.



Category	Model number	Serial number	System ID	SW Relations
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	

9) Input Kairos Core System ID.




License Model	Key code	Release
AT-SF001	SF001-20E0T-23000-9TBEB-84C78	Release
AT-SF002	SF002-20E0T-23000-9TLBF-98182	Release
AT-SF003	SF003-20E0T-23000-9TRAD-ES48B	Release
AT-SF004	SF004-20E0T-23000-9TEEN-CE00E	Release
AT-SF005	SF005-20E0T-23000-9TJD-338BA	Release


System ID : 16 alphanumeric characters (fixed length)











10) Click "Update" button, and click "OK" button in the confirmation screen.

After performing the activation issuing the certificate file in the following step 11) and 12), the setting made in step 5) and 9) cannot be changed. Open the "License Attached" screen in step 8), and please check the settings again.

- In case the link between the license and Kairos Core(AT-KC100) is incorrect:  
Click the "Release" button on the "License Attached" screen and set again from step 4).
- In case the value of Kairos Core System ID is incorrect:  
Edit the value of System ID on the "License Attached" screen.

11) Click  button in the "Certification" column of the "AT-KC100" line.



Category	Model number	Serial number	System ID	Certification
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	
SW	20090918	00000000	00000000	

It will be in the standby state for execution of activation and issuance of registration certificate.

[Continued on next page](#)

# 11. Option software activation [Link to Kairos Core] (3/3)

19/28

## Items to use





Activation PC



USB memory

## [Continuation from the previous page](#)


- 12) Click “OK” button to move to the “Certification download” screen.  
Download certificate file in the Activation PC.  
 (“Downloads” folder etc.)



- 13) Copy the certificate file in the USB memory.  
(AT-KC100\_xxxx\_Certification.LST)

The System ID registered in step 9) is described in “xxxx” part.  
This certificate file can only be installed on the Kairos Core with a  
System ID of “xxxx”.

 Kairos Core  
System ID  
(memo)

 Kairos Core  
Serial Number  
(memo)

# 12. Option software certificate file installation (1/2)

20/28

## Items to use




GUI PC




USB memory

AT-KC100\_XXXX\_  
Certification.LST


- 1) Launch the Kairos Creator application.
- 2) Help -> install License




- 3) Click "Select License" to display "License File" screen.




- 4) Select the certificate file and click "Open" button.  
(AT-KC100\_XXXX\_Certification.LST)



- 5) Click "Install License".



- 6) Installation is complete when the message "License option upload completed." appears.  
The installed license options are displayed.



[Continued on next page](#)

# 12. Option software certificate file installation (2/2)

21/28

## Items to use



GUI PC




USB memory

AT-KC100\_xxxx\_  
Certification.LST

[Continuation from the previous page](#)

7) Please execute "Settings > export environment file..." on the Kairos Creator menu and save the environment file (.env) **right after the license option installation.**



# Activation procedure for Touch Control Panel

A similar procedure to the Kairos Creator activation procedure is required.  
It is also possible to activate on the same PC as Kairos Creator.

# 13. Touch Control Panel installation, Get GUI PC System ID

23/28

## Items to use



GUI PC



USB memory


xxxx\_setup.exe

1) Launch the GUI PC and execute Touch Control Panel installer.  
(kairos-touch-control-xxxx-win64-setup.exe)

2) Launch Touch Control Panel application.



3) Double clicking on the System-Id string in the About screen,  
select "COPY" with mouse right click.  
Get the GUI PC System ID. (memo)



GUI PC  
System ID  
(memo)

GUI PC System ID (16 alphanumeric characters) will be used in the process of "5. Registration of Kairos Creator". Please store this information in the electric file.

4) Close the Touch Control Panel application.

# 14. GUI PC registration

24/28

Items to use




Activation PC


1) Login to PASS KAIROS.(w/ ID, password)

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)

2) Click “Hardware” button at the side bar menu.




3) Select Country/Area.



4) Input necessary information.


Shop, Country, Model number(TOUCH),  
Serial number(PC name), Date of purchase, Purpose



Select “TOUCH” as a  
Model number.  
Register any string up to 16  
alphanumeric characters for  
the PC name as a Serial  
number.

Already registered PC  
names cannot be used.  
(including other users') If  
they are duplicated, an  
error message will be  
displayed. Please change  
the PC name.

5) Click “Complete registration” button.



\*\*\*  
Please refer to the Remark.

6) Log out from PASS KAIROS system automatically.  
An email of registration notice will be sent to you.

[Remark]  
You can also register  
other equipment and  
license by using “\*\*\*”  
marked buttons. However,  
only the GUI PC is  
registered here.  
For other equipment and  
licenses, please use the  
“Modify/add equipment”  
and “Modify/add license”  
screens described on the  
following pages.



# 15. Touch Control Panel registration

25/28

Items to use



Activation PC

1) Login to PASS KAIROS.(w/ ID, password)

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)

2) Click "Modify/add license" link at the side bar menu.

3) Input necessary information and click "Add" button.

Shop, Country, Model number(AT-SFTC10),  
Key Code, Date of purchase, Purpose

\*Select "AT-SFTC10" in the Model number drop-down list

4) Click "OK" button and software license registration completed.

Registration completed

Software License

AT-SFTC10

Kairos Touch Control Panel

# 16. Touch Control Panel activation [Link to GUI PC] (1/2)

26/28

## Items to use



## Activation PC

GUI PC's  
System ID  
(memo)


\*\*GUI PC and Touch Control Panel need to be registered.


1) Login to PASS KAIROS.(w/ ID, password)

[https://panasonic.biz/sav/kairos\\_e/](https://panasonic.biz/sav/kairos_e/)


2) Click "Search equipment" link at the side bar menu.

3) Click "Search" button to display a list of registered products.


Click  button in the "Unit model" column of the "AT-SFTC10" line.




4) Select the target PC name in the "Unit model" drop-down list, and click "Update" button.




**Link Touch Control Panel software license (AT-SFTC10) to GUI PC.**

5) Click  button in the "SW Relations" column of the "TOUCH" line.



6) Input GUI PC System ID and click "Update" button.



System ID : 16 alphanumeric characters (fixed length)

After performing the activation issuing the certificate file in the following step 7) and 8), the setting made in step 4) and 6) cannot be changed. Open the "License Attached" screen in step 5), and please check the settings again.

- In case the link between the license and Touch Control Panel (PC) is incorrect: Click the "Release" button on the "License Attached" screen and set again from step 3).
- In case the value of System ID is incorrect: Edit the value of System ID on the "License Attached" screen.

[Continued on next page](#)

# 16. Touch Control Panel activation [Link to GUI PC] (2/2)

27/28

## Items to use




Activation PC



USB memory

## [Continuation from the previous page](#)

7) Click  button in the "Certification" column of the "TOUCH" line.



It will be in the standby state for execution of activation and issuance of registration certificate.

8) Click "OK" button to move to the "Certification download" screen.  
Download certificate file in the Activation PC.  
("Downloads" folder etc.)



9) Copy the certificate file in the USB memory.  
(Touch\_xxxx\_Certification.LST)

The System ID registered in step 6) is described in "xxxx" part.  
This certificate file can only be installed on a Touch Control Panel with a System ID of "xxxx".

# 17. Touch Control Panel certificate file installation

28/28

## Items to use



GUI PC




USB memory

Touch\_xxxx\_  
Certification.LST


- 1) Launch the Touch Control Panel application.  
Click "Select" on the About screen.



- 3) Click "Install".



- 2) Select the certificate file created in the process of "Touch Control Panel activation"  
(Touch\_xxxx\_Certification.LST)



- 4) Touch Control Panel launches and installation complete.

